

15. Constant coefficient second order linear ODEs (part 2)

(Notes on Diffy Qs, 2.2)

Jiří Lebl

Oklahoma State University

The textbook: <https://www.jirka.org/diffyqs/>

Review: Given $ay'' + by' + cy = 0$

Try $y = e^{rx}$: $ar^2e^{rx} + bre^{rx} + ce^{rx} = 0$

Review: Given $ay'' + by' + cy = 0$

Try $y = e^{rx}$: $ar^2e^{rx} + bre^{rx} + ce^{rx} = 0$

Divide by e^{rx} to get the *characteristic equation* of the ODE:

$$ar^2 + br + c = 0.$$

Review: Given $ay'' + by' + cy = 0$

Try $y = e^{rx}$: $ar^2e^{rx} + bre^{rx} + ce^{rx} = 0$

Divide by e^{rx} to get the *characteristic equation* of the ODE:

$$ar^2 + br + c = 0.$$

Solve for the r : $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a}.$

Review: Given $ay'' + by' + cy = 0$

Try $y = e^{rx}$: $ar^2e^{rx} + bre^{rx} + ce^{rx} = 0$

Divide by e^{rx} to get the *characteristic equation* of the ODE:

$$ar^2 + br + c = 0.$$

Solve for the r : $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a}.$

$\Rightarrow e^{r_1x}$ and e^{r_2x} are linearly independent solutions.

Review: Given $ay'' + by' + cy = 0$

Try $y = e^{rx}$: $ar^2e^{rx} + bre^{rx} + ce^{rx} = 0$

Divide by e^{rx} to get the *characteristic equation* of the ODE:

$$ar^2 + br + c = 0.$$

Solve for the r : $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a}.$

$\Rightarrow e^{r_1x}$ and e^{r_2x} are linearly independent solutions.

If $r = r_1 = r_2$, then e^{rx} and xe^{rx} are linearly independent solutions.

Review: Given $ay'' + by' + cy = 0$

Try $y = e^{rx}$: $ar^2e^{rx} + bre^{rx} + ce^{rx} = 0$

Divide by e^{rx} to get the *characteristic equation* of the ODE:

$$ar^2 + br + c = 0.$$

Solve for the r : $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a}$.

$\Rightarrow e^{r_1x}$ and e^{r_2x} are linearly independent solutions.

If $r = r_1 = r_2$, then e^{rx} and xe^{rx} are linearly independent solutions.

But, what if the characteristic equation has no real roots? E.g., $r^2 + 1 = 0$.

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then i^2

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1)$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0)$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i = 8i + 12(-1) - 5i$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i = 8i + 12(-1) - 5i = -12 + 3i$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i = 8i + 12(-1) - 5i = -12 + 3i$

Example: $(3 + 2i)(3 - 2i)$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i = 8i + 12(-1) - 5i = -12 + 3i$

Example: $(3 + 2i)(3 - 2i) = 3^2 - (2i)^2$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i = 8i + 12(-1) - 5i = -12 + 3i$

Example: $(3 + 2i)(3 - 2i) = 3^2 - (2i)^2 = 3^2 + 2^2 = 13$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i = 8i + 12(-1) - 5i = -12 + 3i$

Example: $(3 + 2i)(3 - 2i) = 3^2 - (2i)^2 = 3^2 + 2^2 = 13$

Example: $\frac{1}{3 - 2i}$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i = 8i + 12(-1) - 5i = -12 + 3i$

Example: $(3 + 2i)(3 - 2i) = 3^2 - (2i)^2 = 3^2 + 2^2 = 13$

Example: $\frac{1}{3 - 2i} = \frac{1}{3 - 2i} \frac{3 + 2i}{3 + 2i}$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i = 8i + 12(-1) - 5i = -12 + 3i$

Example: $(3 + 2i)(3 - 2i) = 3^2 - (2i)^2 = 3^2 + 2^2 = 13$

Example: $\frac{1}{3 - 2i} = \frac{1}{3 - 2i} \frac{3 + 2i}{3 + 2i} = \frac{3 + 2i}{13}$

$r^2 + 1 = 0$ has *complex* roots. If i is such that $i^2 = -1$, then $i^2 + 1 = 0$ and $(-i)^2 + 1 = 0$.

Remark: Engineers sometimes use j instead of i .

More generally, *complex* numbers are just a pair of real numbers (a, b) , where we decree that

$$(a, b) + (c, d) \stackrel{\text{def}}{=} (a + c, b + d) \quad \text{and} \quad (a, b) \times (c, d) \stackrel{\text{def}}{=} (ac - bd, ad + bc)$$

For real numbers we say $a = (a, 0)$, and we write $i = (0, 1)$.

Then $i^2 = i \times i = (0, 1) \times (0, 1) = (-1, 0) = -1$.

We write $a + ib = (a, b)$.

a is the *real part*, write $\text{Re}(a + ib) = a$.

b is the *imaginary part*, write $\text{Im}(a + ib) = b$.

Example: $(2 + 3i)(4i) - 5i = (2 \times 4)i + (3 \times 4)i^2 - 5i = 8i + 12(-1) - 5i = -12 + 3i$

Example: $(3 + 2i)(3 - 2i) = 3^2 - (2i)^2 = 3^2 + 2^2 = 13$

Example: $\frac{1}{3 - 2i} = \frac{1}{3 - 2i} \frac{3 + 2i}{3 + 2i} = \frac{3 + 2i}{13} = \frac{3}{13} + \frac{2}{13}i$.

The exponential should satisfy $e^{x+y} = e^x e^y$.

The exponential should satisfy $e^{x+y} = e^x e^y$.

So $e^{a+ib} = e^a e^{ib}$.

The exponential should satisfy $e^{x+y} = e^x e^y$.

So $e^{a+ib} = e^a e^{ib}$.

Euler's formula: $e^{i\theta} = \cos \theta + i \sin \theta$ and $e^{-i\theta} = \cos \theta - i \sin \theta$

The exponential should satisfy $e^{x+y} = e^x e^y$.

So $e^{a+ib} = e^a e^{ib}$.

Euler's formula: $e^{i\theta} = \cos \theta + i \sin \theta$ and $e^{-i\theta} = \cos \theta - i \sin \theta$

$\Rightarrow e^{a+ib}$

The exponential should satisfy $e^{x+y} = e^x e^y$.

So $e^{a+ib} = e^a e^{ib}$.

Euler's formula: $e^{i\theta} = \cos \theta + i \sin \theta$ and $e^{-i\theta} = \cos \theta - i \sin \theta$

$\Rightarrow e^{a+ib} = e^a e^{ib}$

The exponential should satisfy $e^{x+y} = e^x e^y$.

So $e^{a+ib} = e^a e^{ib}$.

Euler's formula: $e^{i\theta} = \cos \theta + i \sin \theta$ and $e^{-i\theta} = \cos \theta - i \sin \theta$

$$\Rightarrow e^{a+ib} = e^a e^{ib} = e^a (\cos b + i \sin b)$$

The exponential should satisfy $e^{x+y} = e^x e^y$.

So $e^{a+ib} = e^a e^{ib}$.

Euler's formula: $e^{i\theta} = \cos \theta + i \sin \theta$ and $e^{-i\theta} = \cos \theta - i \sin \theta$

$$\Rightarrow e^{a+ib} = e^a e^{ib} = e^a (\cos b + i \sin b) = e^a \cos b + i e^a \sin b$$

The exponential should satisfy $e^{x+y} = e^x e^y$.

So $e^{a+ib} = e^a e^{ib}$.

Euler's formula: $e^{i\theta} = \cos \theta + i \sin \theta$ and $e^{-i\theta} = \cos \theta - i \sin \theta$

$$\Rightarrow e^{a+ib} = e^a e^{ib} = e^a (\cos b + i \sin b) = e^a \cos b + i e^a \sin b$$

Exercise: Check the identities: $\cos \theta = \frac{e^{i\theta} + e^{-i\theta}}{2}$ and $\sin \theta = \frac{e^{i\theta} - e^{-i\theta}}{2i}$.

The exponential should satisfy $e^{x+y} = e^x e^y$.

So $e^{a+ib} = e^a e^{ib}$.

Euler's formula: $e^{i\theta} = \cos \theta + i \sin \theta$ and $e^{-i\theta} = \cos \theta - i \sin \theta$

$$\Rightarrow e^{a+ib} = e^a e^{ib} = e^a (\cos b + i \sin b) = e^a \cos b + i e^a \sin b$$

Exercise: Check the identities: $\cos \theta = \frac{e^{i\theta} + e^{-i\theta}}{2}$ and $\sin \theta = \frac{e^{i\theta} - e^{-i\theta}}{2i}$.

Remark: Most trig identities follow from $e^{z+w} = e^z e^w$ for complex numbers.

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a}$

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

Write $y_1 = e^{(\alpha+i\beta)x}$

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

Write $y_1 = e^{(\alpha+i\beta)x} = e^{\alpha x} \cos(\beta x) + ie^{\alpha x} \sin(\beta x),$

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

Write $y_1 = e^{(\alpha+i\beta)x} = e^{\alpha x} \cos(\beta x) + ie^{\alpha x} \sin(\beta x), \quad y_2 = e^{(\alpha-i\beta)x}$

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

Write $y_1 = e^{(\alpha+i\beta)x} = e^{\alpha x} \cos(\beta x) + ie^{\alpha x} \sin(\beta x)$, $y_2 = e^{(\alpha-i\beta)x} = e^{\alpha x} \cos(\beta x) - ie^{\alpha x} \sin(\beta x)$.

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

Write $y_1 = e^{(\alpha+i\beta)x} = e^{\alpha x} \cos(\beta x) + i e^{\alpha x} \sin(\beta x)$, $y_2 = e^{(\alpha-i\beta)x} = e^{\alpha x} \cos(\beta x) - i e^{\alpha x} \sin(\beta x)$.

These are also solutions: $y_3 = \frac{y_1 + y_2}{2}$

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

Write $y_1 = e^{(\alpha+i\beta)x} = e^{\alpha x} \cos(\beta x) + ie^{\alpha x} \sin(\beta x)$, $y_2 = e^{(\alpha-i\beta)x} = e^{\alpha x} \cos(\beta x) - ie^{\alpha x} \sin(\beta x)$.

These are also solutions: $y_3 = \frac{y_1 + y_2}{2} = e^{\alpha x} \cos(\beta x)$

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

Write $y_1 = e^{(\alpha+i\beta)x} = e^{\alpha x} \cos(\beta x) + ie^{\alpha x} \sin(\beta x)$, $y_2 = e^{(\alpha-i\beta)x} = e^{\alpha x} \cos(\beta x) - ie^{\alpha x} \sin(\beta x)$.

These are also solutions: $y_3 = \frac{y_1 + y_2}{2} = e^{\alpha x} \cos(\beta x)$ $y_4 = \frac{y_1 - y_2}{2i}$

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

Write $y_1 = e^{(\alpha+i\beta)x} = e^{\alpha x} \cos(\beta x) + i e^{\alpha x} \sin(\beta x)$, $y_2 = e^{(\alpha-i\beta)x} = e^{\alpha x} \cos(\beta x) - i e^{\alpha x} \sin(\beta x)$.

These are also solutions: $y_3 = \frac{y_1 + y_2}{2} = e^{\alpha x} \cos(\beta x)$ $y_4 = \frac{y_1 - y_2}{2i} = e^{\alpha x} \sin(\beta x)$

$ay'' + by' + cy = 0$ has the characteristic equation $ar^2 + br + c = 0$.

Suppose the roots are complex, that is, $b^2 - 4ac < 0$.

The roots are (quadratic formula) $r_1, r_2 = \frac{-b \pm \sqrt{b^2 - 4ac}}{2a} = \frac{-b}{2a} \pm i \frac{\sqrt{4ac - b^2}}{2a}$.

The roots are always a pair of the form $\alpha \pm i\beta$.

The general solution is $y = C_1 e^{(\alpha+i\beta)x} + C_2 e^{(\alpha-i\beta)x}$.

The exponential is complex valued and so must be C_1, C_2 . Let's do better.

Write $y_1 = e^{(\alpha+i\beta)x} = e^{\alpha x} \cos(\beta x) + i e^{\alpha x} \sin(\beta x)$, $y_2 = e^{(\alpha-i\beta)x} = e^{\alpha x} \cos(\beta x) - i e^{\alpha x} \sin(\beta x)$.

These are also solutions: $y_3 = \frac{y_1 + y_2}{2} = e^{\alpha x} \cos(\beta x)$ $y_4 = \frac{y_1 - y_2}{2i} = e^{\alpha x} \sin(\beta x)$

Theorem

If the characteristic equation has the roots $\alpha \pm i\beta$ (i.e., $b^2 - 4ac < 0$), then the general solution is

$$y = C_1 e^{\alpha x} \cos(\beta x) + C_2 e^{\alpha x} \sin(\beta x).$$

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$,

Example: Solve $y'' + k^2 y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$,

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$,

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$, so $r = 3 \pm 2i$,

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$, so $r = 3 \pm 2i$, the general solution is

$$y = C_1 e^{3x} \cos(2x) + C_2 e^{3x} \sin(2x).$$

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$, so $r = 3 \pm 2i$, the general solution is

$$y = C_1 e^{3x} \cos(2x) + C_2 e^{3x} \sin(2x).$$

$$0 = y(0)$$

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$, so $r = 3 \pm 2i$, the general solution is

$$y = C_1 e^{3x} \cos(2x) + C_2 e^{3x} \sin(2x).$$

$$0 = y(0) = C_1 e^0 \cos 0 + C_2 e^0 \sin 0$$

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$, so $r = 3 \pm 2i$, the general solution is

$$y = C_1 e^{3x} \cos(2x) + C_2 e^{3x} \sin(2x).$$

$$0 = y(0) = C_1 e^0 \cos 0 + C_2 e^0 \sin 0 = C_1$$

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$, so $r = 3 \pm 2i$, the general solution is

$$y = C_1 e^{3x} \cos(2x) + C_2 e^{3x} \sin(2x).$$

$$0 = y(0) = C_1 e^0 \cos 0 + C_2 e^0 \sin 0 = C_1 \quad \Rightarrow \quad C_1 = 0 \text{ and } y = C_2 e^{3x} \sin(2x).$$

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$, so $r = 3 \pm 2i$, the general solution is

$$y = C_1 e^{3x} \cos(2x) + C_2 e^{3x} \sin(2x).$$

$$0 = y(0) = C_1 e^0 \cos 0 + C_2 e^0 \sin 0 = C_1 \quad \Rightarrow \quad C_1 = 0 \text{ and } y = C_2 e^{3x} \sin(2x).$$

$$y' = 3C_2 e^{3x} \sin(2x) + 2C_2 e^{3x} \cos(2x)$$

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$, so $r = 3 \pm 2i$, the general solution is

$$y = C_1 e^{3x} \cos(2x) + C_2 e^{3x} \sin(2x).$$

$$0 = y(0) = C_1 e^0 \cos 0 + C_2 e^0 \sin 0 = C_1 \Rightarrow C_1 = 0 \text{ and } y = C_2 e^{3x} \sin(2x).$$

$$y' = 3C_2 e^{3x} \sin(2x) + 2C_2 e^{3x} \cos(2x) \Rightarrow 10 = y'(0) = 2C_2, \text{ or } C_2 = 5.$$

Example: Solve $y'' + k^2y = 0$, for a constant $k > 0$.

Characteristic equation is $r^2 + k^2 = 0$, roots are $r = \pm ik$, the general solution is

$$y = C_1 \cos(kx) + C_2 \sin(kx).$$

Example: Solve $y'' - 6y' + 13y = 0$, $y(0) = 0$, $y'(0) = 10$.

Characteristic equation is $r^2 - 6r + 13 = 0$.

Complete the square $(r - 3)^2 + 2^2 = 0$, so $r = 3 \pm 2i$, the general solution is

$$y = C_1 e^{3x} \cos(2x) + C_2 e^{3x} \sin(2x).$$

$$0 = y(0) = C_1 e^0 \cos 0 + C_2 e^0 \sin 0 = C_1 \Rightarrow C_1 = 0 \text{ and } y = C_2 e^{3x} \sin(2x).$$

$$y' = 3C_2 e^{3x} \sin(2x) + 2C_2 e^{3x} \cos(2x) \Rightarrow 10 = y'(0) = 2C_2, \text{ or } C_2 = 5.$$

The solution is

$$y = 5e^{3x} \sin(2x)$$

Complex numbers are useful also for the Cauchy–Euler equations.

Exercise: Suppose $(b - a)^2 - 4ac < 0$. Find a formula for the general solution of $ax^2y'' + bxy' + cy = 0$. Hint: Try $y = x^r$ and note $x^r = e^{r \ln x}$.

Complex numbers are useful also for the Cauchy–Euler equations.

Exercise: Suppose $(b - a)^2 - 4ac < 0$. Find a formula for the general solution of $ax^2y'' + bxy' + cy = 0$. Hint: Try $y = x^r$ and note $x^r = e^{r \ln x}$.

Try it with something simple like $x^2y'' + y = 0$.